

DIGILIVE 16


The DIGILIVE 16 offers ultra-compact digital audio mixer combines the power of a hardware mixer with the beauty and simplicity of a touch-screen control surface.

The DIGILIVE 16 is designed to be quick, simple and intuitive to use. In addition to the 7-inch high-resolution touch-screen where you can access all your features, I/O options and effects, the mixer features full 100mm motorised faders that can recall scene settings at a moments notice. Full control is also available remotely via Wi-Fi using your iPad so you are free to mix anywhere in the venue.



INTELLIGENT USER INTERFACE

- > simple to use 1024 x 600 7" touchscreen with clear and informative graphics
- > clear visual representation of all channel and mixer settings
- > use either touchscreen or encoder to adjust any setting
- > 100mm motorized faders, with one touch layer selection
- > solo, mute and channel select buttons for each channel



MIXING MADE EASY

- > input and output channel metering is clear with the high definition screen
- > both input and output levels clearly displayed
- > pre and post fader metering



RECORDING AND PLAYBACK

- > built in media player and recorder
- > playback from either USB
- > record from any smart output



SMART OUTPUTS

- > 16 internal busses with 8 balanced XLR outputs
- > comprehensive routing facilities to maximise mixer flexibility
- > simple and clear selection and routing



ADVANCED ALGORITHMS

- > 4 band fully parametric EQ
- > each band adjustable between 20Hz and 20kHz
- > variable gain and Q, and ability to save EQ library presets
- > automatic real time analysis (RTA) on 31 band graphic equaliser



DYNAMICS AND EFFECTS ON EVERY CHANNEL

- > fully adjustable gate and compression
- > 4 stereo effects available with reverb, delay, modulation and 31 band graphic EQ
- > simple to use and informative visual representation of effect or dynamic
- > depth and gain reduction metering for accurate adjustment



KEY Features

- 16 ANALOGUE INPUTS** 12 mic input and 2 stereo input channels
- 16 INTERNAL** busses available
- 9 MOTORIZED FADERS** for recall and precise control
- 8 STEREO FX** add reverb, delay, modulation or 31 band graphics to busses or channels
- 8 SMART OUTPUTS** each output can be set to any bus
- DIGITAL I/O** USB playback/record, S/PDIF in/out and AES-EBU output
- 7" TOUCH SCREEN** high resolution to clearly see the information you need
- SCENE SAVING** complete desk (except gain) settings can be saved
- IPAD CONTROL** full remote operation from the IOS APP
- EXTERNAL PSU** for reliable noise free operation

Rear Panel

- built in media player and recorder
- playback from either USB
- record from any smart output



“With it's compact form factor, simple easy to use interface, and wifi connectivity, the DIGILIVE 16 is perfect for gigging musicians and small venues.”

Specification

MIC Input	12 channels
LINE Input	8 x XLR/4 x COMBO XLR/JACK
	2 (Stereo) channels
	Two 6.5 stereo Jacks, one 3.5 stereo Jack in parallel with one stereo channel
Master Output	2 Left/Right balanced XLR
Smart Outputs	6 assignable balanced XLR
Internal busses	16
Stereo Monitor	1 TRS Jack output
Headphone	1 TRS Jack output
Screen	7" high definition touch screen
Faders	8 x motorized 100 mm faders + 1 x motorized 100mm fader for L/R mix
Sample Frequency	48kHz
AD/DA	192kHz, 24-bit
DSP	40-bit float point, SHARC processor
iPad Remote control	Yes
Effects	up to 8 assignable effect modules (reverb, modulation, delay, 31 band GEQ with RTA)
Digital input/outputs	
AES/EBU	Output (XLR)
S/PDIF	Input / Output (RCA phono)
USB Interface	2 for playback/recording, scene storage and system updates
Network	yes via WIFI external module
Power	90-240V ~ 50/60Hz power supply 24VDC output
Dimension (W x H x D)	357 x 145 x 480mm
Net Weight	5kg